

MiniTec[®] Digital MultiMeter

Rugged pocket design with 11 Functions

Includes Relative zero, Data Hold and Range Hold

- 4000 counts on large LCD with full function indication
- Measures AC/DC Voltage and Current, Resistance, Capacitance, Frequency and Temperature
- Temperature measurements to 1400°F (760°C)
- Duty Cycle, Continuity and Diode test
- Autoranging with manual range override
- 10A fuse protection
- Overload protection and indication
- Auto power off saves battery life
- Includes protective rubber holster, general purpose bead wire Type K temperature probe, two 1.5V AAA batteries and test leads



Test Leads included for easy measurements

Specifications	MN26T	Basic Accuracy
Display Count	4000 count	
DC Voltage	600V (0.1mV)	±1.0%
AC Voltage	600V (0.1mV)	±1.5%
DC Current	10A (0.1µA)	±1.5%
AC Current	10A (0.1µA)	±1.8%
Resistance	40MΩ (0.1Ω)	±1.2%
Capacitance	200µF (0.001nF)	±3.5%
Frequency	10MHz (0.001Hz)	±1.5%
Temperature	0 to 1400°F (1°) 0 to 760°C (1°)	±3.0%
Duty Cycle	0.1% to 99.9% (0.1%)	±1.2%
Diode/Continuity	Yes	
Dimensions/ Wt	4.8x2.4x1.6" (122x61x40mm)	9.17oz (260g)

Ordering Information:

MN26TAuto Ranging MiniTec[®] Digital MultiMeter

TP873Spare Type K Bead Wire Temperature PRobe (-22 to 572°F/-30 to 300°C)

409992Vinyl Pouch Carrying Case

